

# R&S® SFE100 Test Transmitter Specifications



# CONTENTS

<b>Specifications</b> .....	<b>4</b>
RF characteristics .....	4
Frequency .....	4
Reference frequency .....	4
Level.....	5
Spectral purity.....	5
RF characteristics with the R&S®SFE100-B90 option (power amplifier) .....	6
Frequency .....	6
Level.....	6
Spectral purity.....	6
RF monitor output .....	6
I/Q modulation.....	7
I/Q modulator.....	7
Internal baseband I/Q.....	7
Extended I/Q input (R&S®SFE100-K80 option).....	7
Digital baseband .....	8
Internal test signals .....	8
MPEG-2 inputs .....	8
TS generator (R&S®SFE100-K20 option) .....	8
TRP player (R&S®SFE100-K22 option).....	8
Analog baseband.....	9
Analog video/audio input.....	9
Audio player .....	9
Internal audio signal generator.....	9
Internal NICAM audio signal generator .....	9
Internal video signal generator (R&S®SFE100-K23 option) .....	10
Digital modulation systems .....	12
Terrestrial standards .....	12
DVB-T2 (R&S®SFE100-K16 option).....	12
DVB-T/DVB-H (R&S®SFE100-K1 option).....	12
T-DMB/DAB (R&S®SFE100-K11 option) .....	13
DTMB (R&S®SFE100-K12 option) .....	13
CMMB (R&S®SFE-K15 option).....	13
MediaFLO™ (R&S®SFE100-K10 option) .....	13
ATSC/8VSB (R&S®SFE100-K4 option).....	14
ATSC-M/H (R&S®SFE100-K18 option) .....	14
ISDB-T/ISDB-T <sub>SB</sub> /ISDB-T <sub>B</sub> (R&S®SFE100-K6 option).....	14

Cable standards .....	15
DVB-C2 (R&S®SFE100-K17 option) .....	15
DVB-C/ISDB-C (R&S®SFE100-K2 option) .....	16
J.83/B (R&S®SFE100-K5 option) .....	16
Satellite standards .....	17
DVB-S/DVB-DSNG (R&S®SFE100-K3 option).....	17
DVB-S2 (R&S®SFE100-K8 option).....	17
DIRECTV legacy modulation (R&S®SFE100-K9 option).....	17
ARB/waveforms .....	18
Arbitrary waveform generator (R&S®SFE100-K35 option).....	18
Analog modulation systems .....	19
AM/FM/RDS (R&S®SFE100-K170 option) .....	19
Standard B/G (R&S®SFE100-K190 option).....	20
Standard D/K (R&S®SFE100-K191 option) .....	21
Standard I (R&S®SFE100-K192 option) .....	22
Standard M/N (R&S®SFE100-K193 option).....	23
Standard L (R&S®SFE100-K194 option) .....	24
ATV multistandard (R&S®SFE-K195 option) .....	24
Internal NICAM encoder .....	24
Simulation .....	25
AWGN generator (R&S®SFE100-K40 option) .....	25
Trigger inputs/outputs .....	25
General data .....	25
System data .....	25
Operating data.....	26
<b>Ordering information .....</b>	<b>27</b>

## Specifications

Specifications apply under the following conditions: 60 minutes warm-up time at ambient temperature, specified environmental conditions met, calibration cycle adhered to and all internal automatic adjustments performed. "Typical values" are designated with the abbreviation "typ.". These values are verified during the final test but are not assured by Rohde & Schwarz. "Nominal values" are design parameters that are not assured by Rohde & Schwarz. These values are verified during product development but are not specifically tested during production.

Rohde & Schwarz equipment is designed for reliable operation up to an altitude of 2000 m above sea level and for transport up to an altitude of 4500 m above sea level.

## RF characteristics

### Frequency

Frequency range		100 kHz to 2.7 GHz
Uncertainty	internal reference	see "reference frequency"
	external reference <sup>1</sup>	< $0.5 \times 10^{-9}$ typ. $1.0 \times 10^{-10}$
Resolution of setting		1 Hz
Setting time	to within $< 1 \times 10^{-7}$ with GUI update stopped	20 ms

### Reference frequency

Uncertainty		< $1.6 \times 10^{-7}$
Aging	after 10 days of uninterrupted operation	< $1.0 \times 10^{-9}$ /day
Temperature effect	in operating temperature range 0 °C to +50 °C	< $5 \times 10^{-8}$
Input for external reference signal	frequency (sine wave)	10 MHz
	maximum deviation	$3 \times 10^{-6}$
	input level	$\geq -5$ dBm to $\leq 19$ dBm
	limits recommended	0 dBm to 19 dBm
	input impedance	50 $\Omega$ /high-impedance, settable
Output for internal reference signal	connector	BNC female, rear
	frequency (sine wave)	10 MHz
	level	typ. +6 dBm, $\pm 3$ dB
	load impedance	> 200 $\Omega$
	connector	9-pin D-Sub female on rear panel, BNC female on rear panel (on request), alternatively trigger out

<sup>1</sup> Averaged over 10 minutes measurement time, 10 minutes after switching to external reference.

**Level**

RF output	connector	N female, front
	output impedance	50 $\Omega$
Maximum level	$f \leq 1.0$ GHz	+15 dBm (PEP) <sup>2</sup>
	1.0 GHz < $f \leq 2.0$ GHz	+12 dBm (PEP)
	2.0 GHz < $f \leq 2.5$ GHz	+10 dBm (PEP)
	2.5 GHz < $f$	+7 dBm (PEP)
Setting range	level	-110 dBm to +20 dBm
	resolution	0.1 dB
Dynamic range of attenuator		110 dB
Level uncertainty	“auto” attenuator mode, temperature range +18 °C to +33 °C	< $\pm 1.0$ dB
Output matching VSWR in 50 $\Omega$ system	at maximum level	< 1.8, typ. < 1.5
	at maximum level – 15 dB	< 1.5, typ. < 1.3
Setting time	to < 0.1 dB deviation from final value; with GUI update stopped, without R&S®SFE100-B90	10 ms
Uninterruptible level setting	“fixed” attenuator mode, setting range	18 dB
Back-feed (from $\geq 50$ $\Omega$ source)	maximum permissible RF power in output frequency range of RF path	+30 dBm, permanent
	permissible DC voltage	$\pm 20$ V

**Spectral purity**

Harmonics	level $\leq 12$ dBm, CW	< -30 dBc
Nonharmonics	level $\geq -20$ dBm, CW	
	carrier frequency, carrier offset > 10 kHz	reference: signal power
	100 kHz to 87 MHz	< -50 dBc
	> 87 MHz to 1 GHz	< -60 dBc
Broadband noise	> 1 GHz to 2.5 GHz	< -50 dBc
	carrier offset > 10 MHz, measurement bandwidth 1 Hz	
	$f > 87$ MHz	< -135 dBc
SSB phase noise	$f \leq 87$ MHz	< -115 dBc
	carrier offset 20 kHz, measurement bandwidth 1 Hz	
	$f \leq 87$ MHz	< -100 dBc
	87 MHz < $f < 375$ MHz	< -110 dBc
	375 MHz $\leq f < 750$ MHz	< -100 dBc
	750 MHz $\leq f < 1$ GHz	< -100 dBc
	$f > 1$ GHz	< -95 dBc
	carrier offset 500 kHz, measurement bandwidth 1 Hz	
	$f \leq 87$ MHz	< -100 dBc
	87 MHz < $f < 375$ MHz	< -130 dBc
	375 MHz $\leq f < 750$ MHz	< -130 dBc
	750 MHz $\leq f < 1$ GHz	< -120 dBc
	$f > 1$ GHz	< -115 dBc

<sup>2</sup> PEP = peak envelope power (CW); for other modulation modes, depending on back-off.

## RF characteristics with the R&S® SFE100-B90 option (power amplifier)

### Frequency

Frequency range	47 MHz to 862 MHz
-----------------	-------------------

### Level

RF output	connector	N female, rear
	output impedance	50 $\Omega$
Maximum level		$\geq +27$ dBm (RMS)
Setting range	level	$-10$ dBm to $+30$ dBm (RMS)
	resolution	0.1 dB
Level uncertainty	“auto” attenuator mode, temperature range $+18$ °C to $+33$ °C	$< \pm 1.5$ dB
VSWR tolerance	in output frequency range	max. 10:1
	maximum permissible DC voltage	0 V
Linearity	shoulder distance in digital modulation systems, level $+27$ dBm	typ. 40 dB (DVB-T)

### Spectral purity

Harmonics	level $\leq 12$ dBm, CW	$< -30$ dBc
	level $\leq 27$ dBm	$< -20$ dBc

### RF monitor output <sup>3</sup>

RF monitor output	connector	BNC female, front
	output impedance	50 $\Omega$
Level	level ratio to RF output on rear panel	$-50$ dB $\pm 5$ dB
Back-feed (from $\geq 50$ $\Omega$ source)	maximum permissible RF power in output frequency range of RF path	0 dBm, permanent
	permissible DC voltage	0 V

<sup>3</sup> The amplifier input signal can be checked at the monitor output.

## I/Q modulation

### I/Q modulator

Modulation frequency range		DC to 35 MHz
Modulation frequency response <sup>4</sup>	up to 35 MHz	< ±2 dB
	up to 5 MHz	< ±0.4 dB
Carrier leakage	without input signal, referenced to full-scale input <sup>5</sup>	< -55 dBc typ. < -65 dBc after local adjustment
Sideband suppression	modulation frequency ≤ 100 kHz, referenced to signal power	< -50 dBc typ. < -60 dBc after local adjustment
I/Q swap	I and Q signals swapped	on, off

### Internal baseband I/Q

Signal characteristics		see "Digital modulation systems"
D/A converter	sample rate	100 MHz
	resolution	16 bit
	sampling rate	400 MHz (internal interpolation × 4)
Aliasing filter	with amplitudes, group delay and Si correction	
	bandwidth 0.1 dB	35 MHz

### Extended I/Q input (R&S<sup>®</sup>SFE100-K80 option)

The R&S<sup>®</sup>SFE100-K80 option allows external digital signals to be fed into the baseband signal processing of the R&S<sup>®</sup>SFE100.

Digital I/Q input	connector	Mini D Ribbon, 26 pins, rear
	level	LVDS
	word width	16 bit
	analog bandwidth	0 Hz to 35 MHz
	symbol rate	3 ksymbol/s to 100 Msymbol/s

<sup>4</sup> This frequency response is superimposed on all frequency responses of this specification.

<sup>5</sup> Value applies after 1 h warm-up time and recalibration for 4 h of operation as well as temperature variations of less than +5 °C.

## Digital baseband

### Internal test signals

MPEG-2 TS packet	header + 184 byte payload PID = 1FFF(hex)	payload: PRBS
MPEG-specific TS packet	sync byte + 187 byte payload	payload: PRBS
DIRECTV TS packet	header + 127 byte payload	payload: PRBS
DIRECTV TS packet without header	130 byte payload	payload: PRBS
PRBS	PRBS in line with ITU-T O.151	$2^{23} - 1$ , $2^{15} - 1$ (selectable)

### MPEG-2 inputs

ASI/SMPTE310M/ETI serial input	connector	BNC female, 2 × rear
	ASI input level	200 mV to 880 mV
	SMPTE310M input level	400 mV to 880 mV
	ETI input level	0 V to $\pm 2.37$ V (HDB3)
	input impedance	75 $\Omega$
	ASI data rate	270 Mbit/s
	SMPTE310M data rate	19.392658 Mbit/s
	ETI data rate	2048 kbit/s
Stuffing	ASI, SMPTE310M	on/off
	stuffing packets	see MPEG-2 TS packets under "Internal test signals"
Display	measured values	packet length, input data rate, useful data rate

### TS generator (R&S®SFE100-K20 option)

Transport stream	files	Rohde & Schwarz data streams	
	file format	generated transport streams (GTS) format	
	length of transport stream packets	ATSC	188
		DVB	188
		sequence length	generation of endless and seamless transport streams with repetition of video, audio and data contents
	data rate	100 kbit/s to 214 Mbit/s (including null packets)	
	net data rate	max. 90 Mbit/s	
	data volume	max. 80 Mbyte payload	
	Signal set		moving picture sequences and test patterns with test tones, for 625 and 525 lines; DVB/ATSC systems, additional signals via options

### TRP player (R&S®SFE100-K22 option)

Replay	file format	TRP, T10, BIN, ETI (any recorded data streams)
	length of transport stream packets	corresponding to externally applied/recorded transport stream
	replay time/sequence length	endless (but not seamless) replay with cut at transition from end of file to beginning of file; seamless in case of TRP file
	data rate	corresponding to recording data rate and setting (100 kbit/s to max. 90 Mbit/s) from hard disk
	data volume	corresponding to recorded data volume, limited only by hard disk size



## Analog baseband

### Analog video/audio input

Video input	connector	BNC female, rear
	CCVS input level	$V_{pp} = 1 \text{ V}$
	input impedance	75 $\Omega$
	level clamping	back-porch clamping
Audio inputs 1/2	connector	9-pin D-Sub female, rear
	input level	100 mV to 1.55 V (RMS)
	input impedance	600 $\Omega$ , balanced
BTSC	connector	9-pin D-Sub female, rear
	input level	0.25 V to 2 V (RMS)
	input impedance	75 $\Omega$

### Audio player

Waveform memory	sequence duration	up to 5 minutes
	resolution	16 bit for AF1 and 16 bit for AF2
Audio	number of signals	2 channels, AF1 and AF2
	bandwidth	DC to 15 kHz
	level	16 bit full scale in each channel corresponds to standard deviation
	frequency response	< $\pm 0.3 \text{ dB}$
Clock generation	clock rate	50 kHz
Marker	position	restart waveform

### Internal audio signal generator

Audio signals	number of signals	2, can be set separately
	frequency	30 Hz to 15 kHz, in 1 Hz steps
	level	-60 dBu to +12 dBu, in 0.01 dB steps, 6 dBu corresponds to standard deviation

### Internal NICAM audio signal generator

Audio signals	number of signals	2, can be set separately
	frequency	30 Hz to 15 kHz, in 1 Hz steps
	level	-60 dBu to +12 dBu, in 0.01 dB steps, 6 dBu corresponds to standard headroom

**Internal video signal generator (R&S® SFE100-K23 option)**

<b>Internal video generator</b>			
Video signals	ATV video basic test signals	COLORBARS_75 (PAL) COLORBARS_75 (PAL M) COLORBARS_75 (PAL N) COLORBARS_75 (NTSC) COLORBARS_75 (SECAM) PAL FuBK	
Insertion test signal structure	in line with country-specific standards		
PAL color bar 75 %	first field		
	line 16	2T pulse	
	line 17	CCIR17	
	line 18	CCIR18/1	
	line 19	CCIR18/2	
	line 20	data line	
	line 21	teletext insertion test signal	
	second field		
	line 327	ramp	
	line 328	modulated ramp	
	line 329	red line	
	line 330	CCIR330/5	
	line 331	CCIR331/1	
	line 332	15 kHz, 100 ns	
	line 333	sin x/x	
line 334	250 kHz, 100 ns		
PAL M color bar 75 %	first field		
	line 16	2T pulse	
	line 17	NTC7 composite	
	line 18	FCC composite	
	second field		
	line 11	ramp	
	line 12	modulated ramp	
	line 13	red line	
	line 14	15 kHz, 125 ns	
	line 15	250 kHz, 125 ns	
	line 16	FCC multiburst	
	line 17	NTC7 combined	
	line 18	sin x/x	
	PAL N color bar 75 %	first field	
		line 16	2T pulse
line 17		CCIR17	
line 18		CCIR18/1	
line 19		CCIR18/2	
line 20		data line	
line 21		teletext insertion test signal	
second field			
line 327		ramp	
line 328		modulated ramp	
line 329		red line	
line 330		CCIR330/5	
line 331		CCIR331/1	
line 332		15 kHz, 100 ns	
line 333		sin x/x	
line 334	250 kHz, 100 ns		

NTSC color bar 75 %	first field		
	line 16	2T pulse	
	line 17	NTC7 composite	
	line 18	FCC composite	
	second field		
	line 11	ramp	
	line 12	modulated ramp	
	line 13	red line	
	line 14	15 kHz, 125 ns	
	line 15	250 kHz, 125 ns	
	line 16	FCC multiburst	
	line 17	NTC7 combined	
	line 18	sin x/x	
	SECAM color bar 75 %	first field	
lines 7 to 15		discriminating signal	
line 16		2T pulse	
line 17		CCIR17	
line 18		CCIR18/1	
line 19		CCIR18/2	
line 20		data line	
line 21		teletext insertion test signal	
second field			
line 327		ramp	
line 328		modulated ramp	
line 329		red line	
line 330		CCIR330/5	
line 331		CCIR331/1	
line 332		15 kHz, 100 ns	
line 333		sin x/x	
line 334		250 kHz, 100 ns	
PAL FuBK		first field	
	line 16	2T pulse	
	line 17	CCIR17	
	line 18	CCIR18/1	
	line 19	CCIR18/2	
	line 20	data line	
	line 21	teletext insertion test signal	
	second field		
	line 327	ramp	
	line 328	modulated ramp	
	line 329	red line	
	line 330	CCIR330/5	
	line 331	CCIR331/1	
	line 332	15 kHz, 100 ns	
	line 333	sin x/x	
	line 334	250 kHz, 100 ns	
	Other video signals	see R&S® ATV Video	

## Digital modulation systems

### Terrestrial standards

#### DVB-T2 (R&S® SFE100-K16 option)

DVB-T2	in line with EN 302755	Europe
Modulation	modulation	COFDM
	PLP number	1 (single PLP) to 16 (multi-PLP)
	bandwidth	1.7 MHz, 5 MHz, 6 MHz, 7 MHz, 8 MHz, (overrange 10 MHz)
	MER	> 40 dB <sup>6</sup>
	modulation frequency response	< ±0.2 dB
	shoulder attenuation	> 45 dB
Coding	baseband mode	normal (NM), high efficiency (HEM)
	code rate	1/2, 3/5, 2/3, 3/4, 4/5, 5/6
	constellation	QPSK, 16QAM, 64QAM, 256QAM
	rotation	on/off
	time interleaver	settable
	FFT mode	1k, 2k, 4k, 8k, 16k and 32k COFDM
	extended carrier mode	on/off
	pilot pattern	PP1, PP2, PP3, PP4, PP5, PP6, PP7, PP8
	guard interval	1/4, 19/128, 1/8, 19/256, 1/16, 1/32, 1/128
	T2 frames per superframe	settable
	OFDM symbols per T2 frame	settable
	PAPR	off, tone reservation (TR) <sup>7</sup>
	Test signals	

#### DVB-T/DVB-H (R&S® SFE100-K1 option)

DVB-T/DVB-H	in line with EN 300744/EN 302304	
Modulation	modulation	COFDM
	bandwidth	5 MHz, 6 MHz, 7 MHz, 8 MHz
	MER	> 40 dB <sup>8</sup>
	modulation frequency response	< ±0.2 dB
	shoulder distance	> 48 dB
	back-off	13.5 dB
Coding	constellation	QPSK, 16QAM, 64QAM, hierarchical coding
	code rate	1/2, 2/3, 3/4, 5/6, 7/8
	guard interval	1/4, 1/8, 1/16, 1/32
	FFT mode	2k, 4k and 8k COFDM
	interleaver	native and in-depth
	TPS	in line with DVB-T/DVB-H
Special functions	Reed-Solomon encoder	can be switched off
Test signals		TS test packet (see "Internal test signals"), PRBS after convolutional encoder

<sup>6</sup> With internal test signals.

<sup>7</sup> Reserved carriers are always modulated with 0+j0.

<sup>8</sup> With internal test signals.

**T-DMB/DAB (R&S® SFE100-K11 option)**

T-DMB/DAB	in line with T-DMB/EN 300401		Korea/Europe
Modulation	modulation	COFDM	
	mode	I, II, III, IV	
	bandwidth	1.536 MHz	
	modulation frequency response	< 0.2 dB	
	shoulder distance	> 45 dB	
	back-off	13 dB	
Single-frequency network	network mode	MFN	
	control	MID, manual	
Special function	PRBS	can be inserted into a subchannel <sup>9</sup>	

**DTMB (R&S® SFE100-K12 option)**

DTMB	in line with GB20600-2006		
Modulation	modulation	COFDM/single carrier	
	bandwidth	6 MHz, 7 MHz, 8 MHz	
	modulation frequency response	< 0.2 dB	
	shoulder distance	> 50 dB	
	back-off	12 dB	
	Coding	constellation	4QAM(QPSK), 4QAM-NR, 16QAM, 32QAM, 64QAM
code rate		0.4, 0.6, 0.8	
guard interval		420, 595, 945 symbols	
guard interval PN		variable/constant	
time interleaver		0, 240, 720 symbols	
FFT mode		4k COFDM/single carrier	
dual pilot tone		on/off (single carrier)	
Network mode	MFN		
Test signals	TS test packet (see "Internal test signals")		

**CMMB (R&S® SFE-K15 option)**

CMMB	in line with GY/T 220.1-2006		
Modulation	modulation	COFDM	
	bandwidth	2 MHz, 8 MHz	
	modulation frequency response	< 0.2 dB	
	shoulder attenuation	> 50 dB	
	Coding	FFT mode	1k, 4k
scrambling mode		0 to 7	
number of timeslots		40	
services			
Reed-Solomon		(240, 240)	
		(240, 224)	
		(240, 192)	
		(240, 176)	
byte interleaver		1 to 3	
LDPC		1/2, 3/4	
constellation	BPSK, QPSK, 16QAM		

**MediaFLO™ (R&S® SFE100-K10 option)**

MediaFLO™	in line with QUALCOMM 80-T0455-1 Rev. E		
Modulation	modulation	COFDM	
	bandwidth	5 MHz, 6 MHz, 7 MHz, 8 MHz	
	modulation frequency response	< 0.2 dB	
	shoulder distance	40 dB	
	back-off	15.5 dB	
	Coding	FFT mode	4k COFDM

<sup>9</sup> Can be inserted into an existing, user-selectable subchannel of an incoming, valid ETI data stream.

**ATSC/8VSB (R&S® SFE100-K4 option)**

ATSC/8VSB	in line with ATSC Doc. A/53 (8VSB)	
Modulation	modulation	8VSB
	bandwidth	6 MHz
	symbol rate	10.762 Msymbol/s
	range	settable $\pm 5\%$
	pilot	1.25
	pulse filtering	root raised cosine rolloff, $\alpha = 0.115$
	MER	> 40 dB
	modulation frequency response	< $\pm 0.25$ dB
	shoulder distance	> 45 dB
	back-off	9 dB
Coding	input data rate	19.392658 Mbit/s
	range	$\pm 5\%$ (depending on symbol rate)
Test signals	TS test packet (see "Internal test signals")	

**ATSC-M/H (R&S® SFE100-K18 option)**

ATSC Mobile DTV ATSC-M/H	in line with ATSC Doc. A/153	mobile TV USA
Modulation	mode	8VSB
	bandwidth	6 MHz
	symbol rate	10.762 Msymbol/s
	range	settable $\pm 5\%$
	pilot	1.25 (can be switched off)
	range	settable (from 0 to 5 in steps of 0.001)
	pulse filtering	root raised cosine rolloff, $\alpha = 0.115$
	MER	> 40 dB 10
	modulation frequency response	< $\pm 0.25$ dB
	shoulder attenuation	> 45 dB
Coding	input data rate	19.392658 Mbit/s
	range	$\pm 5\%$ (depending on symbol rate)
Special functions	randomizer, Reed-Solomon, interleaver, Trellis initialization	can be switched off
Test signals	TS test packet (see "Internal test signals")	

**ISDB-T/ISDB-T<sub>SB</sub>/ISDB-T<sub>B</sub> (R&S® SFE100-K6 option)**

ISDB-T	in line with ARIB STD-B31 version 1.5	
ISDB-T <sub>SB</sub>	in line with ARIB STD-B29 ISDB-T <sub>SB</sub>	
ISDB-T <sub>B</sub>	Brazil	
Modulation	modulation	OFDM
	bandwidth	6 MHz (variable: $\pm 1000$ ppm)
	number of segments	
	STD-B31	13
	STD-B29	1, 3
	MER	> 40 dB
	modulation frequency response	< 0.2 dB
	shoulder distance	> 48 dB
	back-off	13 dB
	Coding	FFT mode
number of layers		1 to 3 (1 or 2 in the case of ISDB-T <sub>SB</sub> )
constellation		QPSK, DQPSK, 16QAM, 64QAM
code rate		1/2, 2/3, 3/4, 5/6, 7/8
guard interval		1/4, 1/8, 1/16, 1/32
time interleaver		0, 1, 2, 4, 8, 16 (additionally 32 with ISDB-T <sub>SB</sub> )
Test signals	TS test packet (see "Internal test signals")	

<sup>10</sup> With internal test signals.

## Cable standards

### DVB-C2 (R&S®SFE100-K17 option)

DVB-C2	in line with EN 302769	
Input	transport stream	
	interface	ASI, SPI
	format	MPEG-2 TS
	PLP	
	number	1 to 4 PLPs
	payload	one live and 3 PRBS
	ID	settable
Modulation	type	normal data PLP
	modulation	OFDM
	mode	16QAM, 64QAM, 256QAM, 1024QAM, 4096QAM
	channel raster bandwidth	6 MHz, 8 MHz
	bundled channels <sup>11</sup>	
	number	1 and 2 channels
	bandwidth	5.71 MHz, 7.61 MHz and 11.42 MHz, 15.22 MHz
	MER	> 40 dB <sup>12</sup>
	modulation frequency response	< ±0.2 dB
	shoulder attenuation	> 45 dB
	Coding	baseband mode
guard interval		1/64, 1/128
BICM		
FEC frame		normal (64k), short (16k)
code rate (concatenated BCH/LDPC)		2/3, 3/4, 4/5, 5/6, 8/9 (short FEC frame), 9/10 (normal FEC frame)
data slice		
number		1 to 4 data slices
ID		settable
packets		type 1, type 2, stuffing
tune position		settable
tune offset		left, right, settable
FEC frame header type		robust, high efficiency (DSlice packets type 2)
XFEC frame number		1 and 2 (DSlice packets type 2)
PLP number		1 to 4 PLP
time interleaving		none, 4 symbols, 8 symbols, 16 symbols
notch types		narrowband, broadband
C2 system		C2 system ID
	network ID	settable
	layer 1 part 2 signaling	
	time interleaving	none, best fit, 4 symbols, 8 symbols
	code rate (concatenated BCH/LDPC)	1/2 (16k LDPC)
Test signals	mode	16QAM
		TS test packet with settable payload (PRBS ITU-T O.151, 0x00, 0xFF) (see "Internal test signals")

<sup>11</sup> In preparation.

<sup>12</sup> With internal test signals.

**DVB-C/ISDB-C (R&S® SFE100-K2 option)**

DVB-C	in line with EN 300429	
ISDB-C	in line with ITU-T J.83/C	
Modulation	modulation	16QAM, 32QAM, 64QAM, 128QAM, 256QAM
	symbol rate	1 Msymbol/s to 8 Msymbol/s, settable
	pulse filtering	root raised cosine rolloff, $\alpha = 0.15, 0.13$
	MER	> 40 dB
	modulation frequency response	$\pm 0.25$ dB
	shoulder distance	> 48 dB
	back-off	9 dB
Special functions	Reed-Solomon encoder	can be switched off
Test signals		TS test packet (see "Internal test signals"), PRBS before mapper

**J.83/B (R&S® SFE100-K5 option)**

J.83/B	in line with ITU-T J.83/B	
Modulation	modulation	64QAM, 256QAM, 1024QAM
	bandwidth	6 MHz
	symbol rate	
	64QAM	5.0569 Msymbol/s
	256QAM	5.3605 Msymbol/s
	1024QAM	5.3605 Msymbol/s
	pulse filtering	root raised cosine rolloff, $\alpha = 0.18$ (64QAM), 0.12 (256/1024QAM)
	MER	> 40 dB
	modulation frequency response	$\pm 0.25$ dB
	shoulder distance	
	64QAM	> 50 dB
	256QAM	> 45 dB
	1024QAM	> 45 dB
back-off	9 dB	
Coding	input data rate	
	64QAM	26.97035 Mbit/s
	256QAM	38.81070 Mbit/s
	1024QAM	49.02525 Mbit/s
	data interleaver	level 1 and level 2
Test signals		TS test packet (see "Internal test signals")



## Satellite standards

### DVB-S/DVB-DSNG (R&S®SFE100-K3 option)

DVB-S/DVB-DSNG	in line with EN 300421/EN 301210	
Modulation	modulation	QPSK, 8PSK, 16QAM
	symbol rate	100 ksymbol/s to 45 Msymbol/s, settable
	pulse filtering	root raised cosine rolloff, $\alpha = 0.35$ variable rolloff (0.25, 0.35)
	MER	38 dB (27.5 Msymbol/s)
	modulation frequency response	$\pm 0.25$ dB
	shoulder distance	> 45 dB
	back-off	9 dB
Coding	code rate	QPSK: 1/2, 2/3, 3/4, 5/6, 7/8
		8PSK: 2/3, 5/6, 8/9
		16QAM: 3/4, 7/8
Special functions	Reed-Solomon encoder	can be switched off
Test signals		TS test packet (see "Internal test signals"), PRBS before convolutional encoder

### DVB-S2 (R&S®SFE100-K8 option)

DVB-S2	in line with EN 302307, broadcast services	
Modulation	modulation	QPSK, 8PSK, 16APSK, 32APSK
	symbol rate	
	QPSK	1 Msymbol/s to 47 Msymbol/s (overrange 53 Msymbol/s)
	8PSK	1 Msymbol/s to 35 Msymbol/s (overrange 40 Msymbol/s)
	16APSK	2 Msymbol/s to 30 Msymbol/s
	32APSK	2 Msymbol/s to 25 Msymbol/s
	pulse filtering	root raised cosine rolloff, $\alpha = 0.20$ variable rolloff (0.15, 0.20, 0.25, 0.35)
	MER	38 dB (20 Msymbol/s)
	modulation frequency response	$\pm 0.25$ dB
	shoulder distance	45 dB
	back-off	12 dB
Coding	code rate	
	QPSK	1/4, 1/3, 2/5, 1/2, 3/5, 2/3, 3/4, 4/5, 5/6, 8/9, 9/10
	8PSK	3/5, 2/3, 3/4, 5/6, 8/9, 9/10
	16APSK	2/3, 3/4, 4/5, 5/6, 8/9, 9/10
	32APSK	3/4, 4/5, 5/6, 8/9, 9/10
	FEC frame	normal (64800 bits)/short (16200 bits)
pilot insertion	can be switched off	
Special functions	error insertion	after CRC-8, BCH or LDPC
Test signals		TS test packet (see "Internal test signals")

### DIRECTV legacy modulation (R&S®SFE100-K9 option)

DIRECTV legacy modulation	in line with DIRECTV transmission specifications	
Modulation	modulation	QPSK
	symbol rate	20 Msymbol/s
	overrange	1 Msymbol/s to 30 Msymbol/s
	pulse filtering	root raised cosine rolloff, $\alpha = 0.20$ variable rolloff (0.15, 0.20, 0.25, 0.35)
	MER	38 dB (20 Msymbol/s)
	modulation frequency response	< $\pm 0.25$ dB
	shoulder distance	45 dB
	back-off	11.5 dB
Coding	code rate	1/2, 2/3, 6/7
Special functions	customer-specific DIRECTV streams	can be replayed in 188-byte format, requires R&S®SFE100-K22 option
	error insertion	after convolutional encoder
Test signals		TS test packet (see "Internal test signals")

## ARB/waveforms

### Arbitrary waveform generator (R&S®SFE100-K35 option)

Waveform memory	length	512 sample to 256 Msample in 1-sample steps
	resolution	2 × 16 bit
	loading time for 10 Msample	3 s
	memory location for data	hard disk
Clock generation	clock rate	400 Hz to 100 MHz
	uncertainty	0.001 Hz
	operating mode	internal
	frequency accuracy (internal)	accuracy of reference frequency
Interpolation	bandwidth	
	with clock rate = 100 MHz (no interpolation), bandwidth 0.1 dB	40 MHz
	with clock rate < 100 MHz, reduction to -0.1 dB	0.31 × clock rate
	sampling rate	automatically interpolated to internal 100 MHz data rate
Triggering	modes	auto
		retrigger
		armed auto
		armed retrigger
	source	internal
		external
delay	0 to 2 <sup>32</sup> - 1 sample, settable	
inhibit	0 to 2 <sup>32</sup> - 1 sample, settable	
Marker	position	restart waveform
	delay	0 to waveform length, settable in samples
Special function	software support	R&S®WinIQSIM™ <sup>13</sup> (R&S®SFE-K350 option)

R&S®SFE100-K35 supports the same waveform libraries as the ARB generator of the R&S®SFU.

T-DMB/DAB waveforms	R&S®SFU-K351	For specifications, see R&S®SFU.
DVB-H waveforms	R&S®SFU-K352	
DRM waveforms	R&S®SFU-K353	
DTV waveforms	R&S®SFU-K354	
MediaFLO™ waveforms	R&S®SFU-K355	
Cable interferers	R&S®SFU-K356	
HD Radio™ waveforms	R&S®SFU-K357	
CMMB waveforms	R&S®SFU-K358	
DVB-T2 waveforms	R&S®SFU-K359	
Analog signals	R&S®SFU-K360	
ISDB-S waveforms	R&S®SFU-K362	
Satellite interferers	R&S®SFU-K363	
MoCA® waveforms	R&S®SFU-K364	
ISDB-Tmm waveforms	R&S®SFU-K365	

<sup>13</sup> With software version 4.24 or later, files generated for the R&S®SFU can also be used for the R&S®SFE100.

## Analog modulation systems

### AM/FM/RDS (R&S®SFE100-K170 option)

FM	FM operating modes	stereo, mono
	audio signals	
	internal audio signal generator	see "Internal audio signal generator"
	external audio input	see "Analog video/audio input"
	AF frequency range	30 Hz to 15 kHz
	AF frequency response	< 0.2 dB
	attenuation at 19 kHz	> 70 dB
	preemphasis	off, 50 µs, 75 µs
	residual AM	< 0.1 % (at AF = 1 kHz, deviation ±50 kHz)
	FM stereo	stereo operating modes
MPX frequency deviation		
deviation		0 Hz to ±100 kHz
resolution		10 Hz
stereo crosstalk attenuation		> 50 dB (at AF = 30 Hz to 15 kHz)
total harmonic distortion <sup>14</sup>		< 0.1 % (at 60 kHz audio frequency deviation, AF = 1 kHz)
SNR (stereo/RDS signal) <sup>14</sup>		at ±40 kHz audio frequency deviation
ITU-R weighted (quasi-peak)		> 64 dB
ITU-R unweighted (RMS)		> 70 dB
pilot tone		
frequency		19 kHz ± 1 Hz
deviation		0 Hz to ±15 kHz
resolution		10 Hz
phase		0° to ±180°
resolution		0.1°
RDS		
subcarrier frequency		57 kHz ± 3 Hz
deviation		0 Hz to ±10 kHz
resolution		10 Hz
FM mono		mono frequency deviation
	deviation	0 Hz to ±100 kHz
	resolution	10 Hz
	total harmonic distortion <sup>15</sup>	< 0.1 % (at ±67.5 kHz audio frequency deviation, AF = 1 kHz)
AM	audio signals	
	internal audio signal generator	see "Internal audio signal generator"
	external audio input	see "Analog video/audio input"
	AF frequency range	30 Hz to 15 kHz
	AF frequency response	< 0.2 dB
	modulation	
	modulation depth	0 % to 100 %
	resolution	1 %
	AM total harmonic distortion	at AF = 1 kHz
	m = 30 %	< 0.2 %
m = 80 %	< 0.2 %	

<sup>14</sup> Generator without preemphasis, receiver with deemphasis.

<sup>15</sup> Generator and receiver without preemphasis/deemphasis.

**Standard B/G (R&S® SFE100-K190 option)**

Standard B/G	in line with country-specific standard		
Vision modulation	modulation	B/G	
	group delay		
	precorrection	CCIR – B/G general half (can be switched off)	
	frequency response	< 20 ns (with/without vestigial sideband filtering)	
	vestigial sideband filtering	B/G, can be switched off	
	amplitude frequency response	< 0.5 dB (–0.6 MHz to +4.8 MHz) (with/without vestigial sideband filtering)	
	residual carrier	0 % to 30 %, settable in 0.1 % steps	
	signal-to-noise ratio video <sup>16</sup>	> 60 dB, weighted	
	back-off	6 dB	
	Sound modulation	operating mode	mono, stereo, dual tone, NICAM, mono/NICAM
		modulation of sound carrier 1, 2	
modulation mode		FM	
frequency deviation		30 kHz (settable)	
preemphasis		50 µs/75 µs (can be switched off)	
vision/sound intercarrier frequency		5.5 MHz/5.74 MHz (settable)	
vision/sound carrier power ratio		13 dB/20 dB (settable)	
pilot tone		in sound carrier 2 (can be switched off)	
signal-to-noise ratio sound		> 60 dB, weighted (CCIR)	
Video signals		internal video signal generator	see R&S® SFE100-K23
	external video input	see “Analog video/audio input”	
Audio signals	internal audio generator	see “Internal audio signal generator” see “Internal NICAM audio signal generator”	
	external audio input	see “Analog video/audio input”	
	audio player	see “Audio player”	

<sup>16</sup> For RF > 87.0 MHz.

**Standard D/K (R&S® SFE100-K191 option)**

Standard D/K	in line with country-specific standard	
Vision modulation	modulation	D/K
	group delay	
	precorrection	OIRT – D/K half (can be switched off)
	frequency response	< 20 ns (with/without vestigial sideband filtering)
	vestigial sideband filtering	DK, DK-FM2, DK-NICAM, can be switched off
	amplitude frequency response	< 0.5 dB (-1 MHz to +5.8 MHz) (with/without vestigial sideband filtering)
	residual carrier	0 % to 30 %, settable in 0.1 % steps
	signal-to-noise ratio	
	video <sup>17</sup>	> 60 dB, weighted
	back-off	6 dB
Sound modulation	operating mode	mono, stereo, dual tone, NICAM, mono/NICAM
	modulation of sound carrier 1, 2	
	modulation mode	FM
	frequency deviation	30 kHz (settable)
	preemphasis	50 µs/75 µs (can be switched off)
	vision/sound intercarrier frequency	6.5 MHz/6.74 MHz (settable)
	vision/sound carrier power ratio	13 dB/20 dB (settable)
	pilot tone	in sound carrier 2 (can be switched off)
	signal-to-noise ratio	
	sound	> 60 dB, weighted (CCIR)
Video signals	internal video signal generator	see R&S® SFE100-K23
	external video input	see "Analog video/audio input"
Audio signals	internal audio generator	see "Internal audio signal generator" see "Internal NICAM audio signal generator"
	external audio input	see "Analog video/audio input"
	audio player	see "Audio player"

<sup>17</sup> For RF > 87.0 MHz.

**Standard I (R&S®SFE100-K192 option)**

Standard I	in line with country-specific standard	
Vision modulation	modulation	I
	group delay	
	precorrection	UK – I (can be switched off)
	frequency response	< 20 ns (with/without vestigial sideband filtering)
	vestigial sideband filtering	I, I1 (can be switched off)
	amplitude frequency response	< 0.5 dB (–1 MHz to +4.8 MHz) (with/without vestigial sideband filtering)
	residual carrier	0 % to 30 %, settable in 0.1 % steps
	signal-to-noise ratio	
	video <sup>18</sup>	> 60 dB, weighted
	back-off	6 dB
Sound modulation	operating mode	mono, mono/NICAM, NICAM
	modulation of sound carrier 1	
	modulation mode	FM
	frequency deviation	30 kHz (settable)
	preemphasis	50 µs/75 µs (can be switched off)
	vision/sound intercarrier frequency	6 MHz (settable)
	vision/sound carrier power ratio	13 dB (settable)
	modulation of sound carrier 2	
	modulation mode	NICAM
	vision/sound intercarrier frequency	6.552 MHz (settable)
	vision/sound carrier power ratio	20 dB (settable)
	signal-to-noise ratio	
	sound	> 60 dB, weighted (CCIR)
Video signals	internal video signal generator	see R&S®SFE100-K23
	external video input	see “Analog video/audio input”
Audio signals	internal audio generator	see “Internal audio signal generator” see “Internal NICAM audio signal generator”
	external audio input	see “Analog video/audio input”
	audio player	see “Audio player”

<sup>18</sup> For RF > 87.0 MHz.

**Standard M/N (R&S®SFE100-K193 option)**

Standard M/N	in line with country-specific standard	
Vision modulation	modulation	M/N
	group delay	
	precorrection	FCC – M/N (can be switched off)
	frequency response	< 20 ns (with/without vestigial sideband filtering)
	vestigial sideband	
	filtering	M, N (can be switched off)
	amplitude frequency response	< 0.5 dB (–0.6 MHz to +4 MHz) (with/without vestigial sideband filtering)
	residual carrier	0 % to 30 %, settable in 0.1 % steps
	signal-to-noise ratio	
	video <sup>19</sup>	> 60 dB, weighted
	back-off	6 dB
Sound modulation	operating mode	BTSC mono, stereo Korea, dual Korea
	modulation of sound carrier 1, 2	
	modulation mode	FM
	frequency deviation	25 kHz (settable)
	preemphasis	50 µs/75 µs (can be switched off)
	vision/sound intercarrier frequency	4.5 MHz/4.742 MHz (settable)
	vision/sound carrier power ratio	13 dB/20 dB (settable)
	pilot tone	in sound carrier 2 (can be switched off)
	signal-to-noise ratio	
	sound	> 60 dB, weighted (CCIR)
Video signals	internal video signal generator	see R&S®SFE100-K23
	external video input	see “Analog video/audio input”
Audio signals	internal audio generator	see “Internal audio signal generator”
	external audio input	see “Analog video/audio input”
	audio player	see “Audio player”

---

<sup>19</sup> For RF > 87.0 MHz.

**Standard L (R&S®SFE100-K194 option)**

Standard L	in line with country-specific standard	
Sound modulation	modulation	L
	group delay	
	precorrection	TDF – L (can be switched off)
	frequency response	< 20 ns (with/without vestigial sideband filtering)
	vestigial sideband	
	filtering	L, L NICAM (can be switched off)
	amplitude frequency response	< 0.5 dB (–1 MHz to +5.8 MHz) (with/without vestigial sideband filtering)
	residual carrier	0 % to 30 %, settable in 0.1 % steps
	signal-to-noise ratio	
	video <sup>20</sup>	> 60 dB, weighted
back-off	6 dB	
Sound modulation	operating mode	AM mono, AM mono/NICAM, NICAM
	modulation of sound carrier 1	
	modulation mode	mono/NICAM
	vision/sound intercarrier frequency	5.85 MHz (settable)
	vision/sound carrier power ratio	27 dB (settable)
	modulation of sound carrier 2	
	modulation mode	AM
	frequency deviation	modulation depth 54 % (settable)
	vision/sound intercarrier frequency	6.5 MHz (settable)
	vision/sound carrier power ratio	10 dB (settable)
Video signals	internal video signal generator	see R&S®SFE100-K23
	external video input	see “Analog video/audio input”
Audio signals	internal audio generator	see “Internal audio signal generator” see “Internal NICAM audio signal generator”
	external audio input	see “Analog video/audio input”
	audio player	see “Audio player”

**ATV multistandard (R&S®SFE-K195 option)**

Standard B/G		see R&S®SFE-K190
Standard D/K		see R&S®SFE-K191
Standard I		see R&S®SFE-K192
Standard M/N		see R&S®SFE-K193
Standard L		see R&S®SFE-K194

**Internal NICAM encoder**

Included in the following options: R&S®SFU-K190, R&S®SFU-K191, R&S®SFU-K193 and R&S®SFU-K194.

Audio coding	input	see “Analog video/audio input” or “Internal NICAM audio signal generator”
	operating mode	mono, stereo, dual tone
	preemphasis	J.17, can be switched off
	headroom (400 Hz)	–6 dB to +6 dB, can be set different from standard
Encoder	data	audio coding, NICAM728 data input, PRBS, NICAM audio generator
	pulse filtering	root raised cosine rolloff, $\alpha = 0.40$ (B/G, D/K, L standards) $\alpha = 1.00$ (I standard)
NICAM728 data input	connector	9-pin D-Sub female, rear
	input level	1 V to 10 V ( $V_{pp}$ )
	input impedance	50 $\Omega$

<sup>20</sup> For RF > 87.0 MHz.



## Simulation

### AWGN generator (R&S®SFE100-K40 option)

Maximum 3 dB spectrum (AWGN)	DVB-T/DVB-H	2.2 × channel bandwidth
	DVB-T2	2.2 × channel bandwidth
	T-DMB/DAB	7.9 MHz
	DTMB	3.6 × channel bandwidth
	CMMB	2.4 × channel bandwidth
	MediaFLO™	1.8 × channel bandwidth
	ATSC/8VSB	20.7 MHz
	ATSC-M/H	20.7 MHz
	ISDB-T/ISDB-T <sub>SB</sub> /ISDB-T <sub>B</sub>	15.6 MHz
	DVB-C/ISDB-C	1.9 × symbol rate
	J.83/B	1.9 × symbol rate
	DVB-S/DVB-DSNG	3.8 × symbol rate
	DVB-S2	80.6 MHz
	DIRECTV	80.6 MHz
	ARB (arbitrary waveform generator)	9.6 × clock frequency
	audio BC	5.5 MHz
	analog TV	25.2 MHz
Noise	density distribution function	Gaussian, statistical, separate for I and Q
	crest factor	18 dB
C/N	setting range	-30 dB to +60 dB
	resolution	0.01 dB
	uncertainty (for system bandwidth = symbol rate and C/N < 20 dB)	< 0.2 dB
System bandwidth (bandwidth for calculating noise power)	range	100 kHz to 80 MHz

### Trigger inputs/outputs

Trigger OUT	connector	9-pin D-Sub female, rear alternatively reference OUT
	load impedance	> 200 Ω
	output level	LVTTTL
1PPS input/trigger IN	connector	BNC female, rear
	input impedance	high impedance
	input level	LVTTTL

## General data

### System data

System	operating system	PC platform
		Windows XP Embedded
		min. 160 Gbyte internal hard disk
Local control	display	LCD 200 × 64 pixel
	control	hardkeys
Remote control	command set	SCPI 1999.5
	Ethernet	10/100BaseT
Connectors	Ethernet	RJ-45, rear
	USB	USB 2.0, front and rear
	AC supply input	IEC 60320 C14, rear

**Operating data**

Power supply	AC input voltage range	100 V to 240 V $\pm$ 10 %
	supply frequency	50 Hz to 60 Hz $\pm$ 5 %
	input current	1.8 to 0.8 A
	power consumption	55 W
	with power amplifier	82 W
Electromagnetic compatibility		in line with EN 55011 class B, EN 61326-1
	power factor correction	in line with EN 61000-3-2
Immunity against RF fields		up to 10 V/m
Environmental conditions	operating temperature range	+5 °C to +45 °C
	permissible temperature range	0 °C to +50 °C
	storage temperature range	-20 °C to +60 °C
	climatic resistance, cyclic test at +25 °C/+40 °C	85 % rel. humidity
Mechanical resistance	vibration, sinusoidal	5 Hz to 150 Hz, max. 2 g at 55 Hz, 55 Hz to 150 Hz, 0.5 g constant, in line with EN 60068-2-6
	vibration, random	10 Hz to 300 Hz, acceleration 1.2 g (RMS), in line with EN 60068-2-64
	shock	40 g shock spectrum, in line with MIL-STD-810E, method 516.4, procedure I
Electrical safety		in line with IEC 61010-1, EN 61010-1 and UL 61010-1, CSA C22.2 No. 61010-1
Dimensions	W $\times$ H $\times$ D	427 mm $\times$ 44 mm $\times$ 450 mm (1 HU) <sup>21</sup> (16.81 in $\times$ 1.73 in $\times$ 17.72 in)
Weight		6 kg (13.28 lb)
Recommended calibration interval		3 years
Standard warranty period		1 year

<sup>21</sup> For rack installation, the use of an additional dummy panel is recommended.

# Ordering information

Option identification: R&S®SFE100-Bxy = hardware option, R&S®SFE100-Kxy = software option.

Order Designation	Type	Order No.
<b>Test Transmitter, model .02</b> For digital standards and ARB generator, including power cable, Quick Start Guide, CD-ROM (includes operating manuals)	R&S®SFE100	2112.4100.02
<b>Test Transmitter, model .12</b> For digital standards, including power cable, Quick Start Guide, CD-ROM (includes operating manuals)	R&S®SFE100	2112.4100.12
<b>Test Transmitter, model .03</b> For digital standards, analog standards, and ARB generator, including power cable, Quick Start Guide, CD-ROM (includes operating manuals)	R&S®SFE100	2112.4100.03
<b>Test Transmitter, model .13</b> For analog standards, including power cable, Quick Start Guide, CD-ROM (includes operating manuals)	R&S®SFE100	2112.4100.13
<b>Options</b>		
<b>Digital modulation systems</b>		
DVB-T/DVB-H Coder	R&S®SFE100-K1	2113.4003.02
DVB-C/ISDB-C Coder	R&S®SFE100-K2	2113.4026.02
DVB-S/DVB-DSNG Coder	R&S®SFE100-K3	2113.4049.02
DVB-S2 Coder	R&S®SFE100-K8	2113.4126.02
ATSC/8VSB Coder	R&S®SFE100-K4	2113.4061.02
J.83/B Coder	R&S®SFE100-K5	2113.4084.02
ISDB-T/ISDB-T <sub>SB</sub> /ISDB-T <sub>B</sub> Coder	R&S®SFE100-K6	2113.4103.02
MediaFLO™ Coder	R&S®SFE100-K10	2113.4161.02
T-DMB/DAB Coder	R&S®SFE100-K11	2113.4184.02
DTMB Coder	R&S®SFE100-K12	2113.4203.02
DIRECTV Legacy Modulation Coder	R&S®SFE100-K9	2113.4149.02
CMMB Coder	R&S®SFE100-K15	2113.4261.02
DVB-T2 Coder requires an installed R&S®SFE100-B15 option	R&S®SFE100-K16	2113.4284.02
DVB-C2 Coder requires an installed R&S®SFE100-B15 option	R&S®SFE100-K17	2113.4303.02
ATSC-M/H Coder	R&S®SFE100-K18	2113.4326.02
<b>Analog modulation systems</b>		
AM/FM/RDS Coder	R&S®SFE100-K170	2113.4426.02
ATV Standard B/G Coder	R&S®SFE100-K190	2113.4649.02
ATV Standard D/K Coder	R&S®SFE100-K191	2113.4661.02
ATV Standard I Coder	R&S®SFE100-K192	2113.4684.02
ATV Standard M/N Coder	R&S®SFE100-K193	2113.4703.02
ATV Standard L Coder	R&S®SFE100-K194	2113.4726.02
ATV Multistandard	R&S®SFE100-K195	2113.4749.02
<b>ARB/waveforms</b>		
ARB Waveform Generator requires an installed R&S®SFE100-B3 option	R&S®SFE100-K35	2113.4926.02
Memory Extension	R&S®SFE100-B3	2112.4400.04
R&S®WinIQSIM™ Support	R&S®SFE100-K350	2113.4949.02
T-DMB/DAB Waveforms can be used with the R&S®SFE100-K35 option	R&S®SFU-K351	2110.4277.04
DVB-H Waveforms can be used with the R&S®SFE100-K35 option	R&S®SFU-K352	2110.4425.02
DRM Waveforms can be used with the R&S®SFE100-K35 option	R&S®SFU-K353	2110.4554.02
DTV Interferers can be used with the R&S®SFE100-K35 option	R&S®SFU-K354	2110.4690.02
MediaFLO™ Waveforms can be used with the R&S®SFE100-K35 option	R&S®SFU-K355	2110.2974.02
Cable Interferers can be used with the R&S®SFE100-K35 option	R&S®SFU-K356	2110.3212.02
HD Radio™ Waveforms can be used with the R&S®SFE100-K35 option	R&S®SFU-K357	on request
CMMB Waveforms can be used with the R&S®SFE100-K35 option	R&S®SFU-K358	2112.3726.02

Order Designation	Type	Order No.
DVB-T2 Waveforms can be used with the R&S®SFE100-K35 option	R&S®SFU-K359	2112.3803.02
Analog Signals can be used with the R&S®SFE100-K35 option	R&S®SFU-K360	2110.3941.02
ISDB-S Waveforms can be used with the R&S®SFE100-K35 option	R&S®SFU-K362	2115.2450.02
Satellite Interferers can be used with the R&S®SFE100-K35 option	R&S®SFU-K363	2115.2537.02
MoCA® Waveforms can be used with the R&S®SFE100-K35 option	R&S®SFU-K364	2115.2920.02
ISDB-Tmm Waveforms can be used with the R&S®SFE100-K35 option	R&S®SFU-K365	2115.3010.02
<b>Baseband inputs/outputs</b>		
Extended I/Q Input	R&S®SFE100-K80	2113.5245.02
<b>Digital baseband</b>		
TS Generator including SDTV streams	R&S®SFE100-K20	2113.4861.02
DVB-H Stream Library requires the R&S®SFE100-K20 option	R&S®DV-DVBH	2085.8704.02
Test Card M Streams requires the R&S®SFE100-K20 option	R&S®DV-TCM	2085.7708.02
HDTV Sequences requires the R&S®SFE100-K20 option	R&S®DV-HDTV	2085.7650.02
H.264 Stream Library requires the R&S®SFE100-K20 option	R&S®DV-H264	2085.9052.02
ISDB-T Stream Library requires the R&S®SFE100-K20 option	R&S®DV-ISDBT	2085.9146.02
TRP Player	R&S®SFE100-K22	2113.5268.02
TS Generator/Player	R&S®SFE100-PK20	2113.6041.02
Basic Stream Library, requires the R&S®SFE100-K22 option	R&S®LIB-K70	2116.9558.02
Extended SDTV Library, requires the R&S®SFE100-K22 option	R&S®LIB-K71	2116.9564.02
Extended HDTV Library, requires the R&S®SFE100-K22 option	R&S®LIB-K72	2116.9570.02
3D TV Library, requires the R&S®SFE100-K22 option	R&S®LIB-K73	2116.9587.02
T-DMB/DAB Streams requires the R&S®SFE100-K22 option	R&S®SFU-K221	2110.4348.02
MediaFLO™ Streams requires the R&S®SFE100-K22 option	R&S®SFU-K222	2110.2968.02
DAB+ Streams requires the R&S®SFE100-K22 option	R&S®SFU-K223	2110.4760.02
Brazilian ISDB-T Transport Streams requires the R&S®SFE100-K22 option	R&S®SFU-K224	2110.4777.02
CMMB Transport Streams requires the R&S®SFE100-K22 option	R&S®SFU-K225	2112.3649.02
ATSC and ATSC Mobile DTV Streams requires the R&S®SFE100-K22 option	R&S®SFU-K226	2110.3812.02
DVB-T2 MI Streams requires the R&S®SFE100-K22 option	R&S®SFU-K227	2115.2120.02
EMC Streams requires the R&S®SFE100-K22 option	R&S®SFU-K228	2115.2520.02
French DMB requires the R&S®SFE100-K22 option	R&S®SFU-K229	2115.2543.02
Customer-Specific Transport Streams	R&S®DV-SCA	on request
<b>Analog baseband</b>		
Video Generator	R&S®SFE100-K23	2113.4884.02
ATV Video Signals	R&S®ATV Video	2110.4831.02

Order Designation	Type	Order No.
<b>Other extras</b>		
VHF/UHF Power Amplifier	R&S®SFE100-B90	2112.4900.02
Coder Extension Board	R&S®SFE100-B15	2112.4222.02
<b>Recommended extras</b>		
Operating manual (English), printed		2112.4122.12
19" Rack Adapter	R&S®ZZA-111	1096.3254.00
Adapter for Telescopic Sliders	R&S®ZZA-T45	1109.3774.00
External USB CD-RW Drive	R&S®PSP-B6	1134.8201.12
LVDS cable for digital I/Q interface, 2 m		1130.1302.00

<b>Service options</b> (can only be ordered in connection with the purchase of an instrument)		
Extended Warranty, one year	R&S®WE1SFE100	Please contact your local Rohde & Schwarz sales office.
Extended Warranty, two years	R&S®WE2SFE100	
Extended Warranty, three years	R&S®WE3SFE100	
Extended Warranty, four years	R&S®WE4SFE100	
Extended Warranty with Calibration Coverage, one year	R&S®CW1SFE100	
Extended Warranty with Calibration Coverage, two years	R&S®CW2SFE100	
Extended Warranty with Calibration Coverage, three years	R&S®CW3SFE100	
Extended Warranty with Calibration Coverage, four years	R&S®CW4SFE100	

#### Extended warranty with a term of one to four years (WE1 to WE4)

Repairs carried out during the contract term are free of charge <sup>22</sup>. Necessary calibration and adjustments carried out during repairs are also covered. Simply contact the forwarding agent we name; your product will be picked up free of charge and returned to you in top condition a couple of days later.

#### Extended warranty with calibration (CW1 to CW4)

Enhance your extended warranty by adding calibration coverage at a package price. This package ensures that your Rohde & Schwarz product is regularly calibrated, inspected and maintained during the term of the contract. It includes all repairs <sup>22</sup> and calibration at the recommended intervals as well as any calibration carried out during repairs or option upgrades.

For product brochure, see PD 5213.9234.12 and [www.rohde-schwarz.com](http://www.rohde-schwarz.com).

<sup>22</sup> Excluding defects caused by incorrect operation or handling and force majeure. Wear-and-tear parts are not included.





## Service you can rely on

- ▮ Worldwide
- ▮ Local and personalized
- ▮ Customized and flexible
- ▮ Uncompromising quality
- ▮ Long-term dependability

## About Rohde & Schwarz

Rohde & Schwarz is an independent group of companies specializing in electronics. It is a leading supplier of solutions in the fields of test and measurement, broadcasting, radiomonitoring and radiolocation, as well as secure communications. Established more than 75 years ago, Rohde & Schwarz has a global presence and a dedicated service network in over 70 countries. Company headquarters are in Munich, Germany.

## Environmental commitment

- ▮ Energy-efficient products
- ▮ Continuous improvement in environmental sustainability
- ▮ ISO 14001-certified environmental management system

Certified Quality System  
**ISO 9001**

## Rohde & Schwarz GmbH & Co. KG

[www.rohde-schwarz.com](http://www.rohde-schwarz.com)

## Regional contact

- ▮ Europe, Africa, Middle East | +49 89 4129 12345  
[customersupport@rohde-schwarz.com](mailto:customersupport@rohde-schwarz.com)
- ▮ North America | 1 888 TEST RSA (1 888 837 87 72)  
[customer.support@rsa.rohde-schwarz.com](mailto:customer.support@rsa.rohde-schwarz.com)
- ▮ Latin America | +1 410 910 79 88  
[customersupport.la@rohde-schwarz.com](mailto:customersupport.la@rohde-schwarz.com)
- ▮ Asia/Pacific | +65 65 13 04 88  
[customersupport.asia@rohde-schwarz.com](mailto:customersupport.asia@rohde-schwarz.com)
- ▮ China | +86 800 810 8228/+86 400 650 5896  
[customersupport.china@rohde-schwarz.com](mailto:customersupport.china@rohde-schwarz.com)

R&S® is a registered trademark of Rohde & Schwarz GmbH & Co. KG  
Trade names are trademarks of the owners | Printed in Germany (bb)  
PD 5213.9234.22 | Version 05.00 | December 2012 | R&S®SFE100

Subject to change

© 2008 - 2012 Rohde & Schwarz GmbH & Co. KG | 81671 München, Germany



5213923422